

# Opsætning data via simkort på SmartBox og MZ Pro3

Hvis du ønsker at køre MZ Pro3 eller SmartBox udelukkende med data fra simkort, så bør du følge denne guide ved opstart.

- Start alarmen op med LAN-kabel i, så I er på samme router.
- Log nu ind på alarmens IP-adresse (fin den evt. vha. Finder)
- **Punkt 1** : Gå i "Network Setting" – "GSM" i venstre side
- **Punkt 2** : "Test present of SIM card" = Yes
- **Punkt 3** : "Time Limit" = No Limit
- **Punkt 4** : Bekræft ændringer med "OK"
- **Punkt 5** : Udfyld teleudbyderens APN
- **Punkt 6** : Bekræft APN med "OK"
- **Punkt 7** : Gå i "System Setting" og "Date & Time" i venstre side
- **Punkt 8** : Fjern flueben og sæt Server = Disable
- Bekræft med "OK"

The screenshot displays the Climax alarm system's web interface. On the left, a navigation menu shows 'Network Setting' > 'GSM' circled in red (1). The main content area is divided into sections: 'GSM' (Status: TELIA DK, Roaming, Signal: 9, IMEI: 356449062164453, IMSI: 238208900), 'Check SIM' (Test present of SIM card: No Yes, with 'Yes' circled in red (2)), 'Time Limit' (Max connection time for IP: No Limit, with 'No Limit' circled in red (3)), 'GPRS' (APN, User, Password fields, with 'OK' circled in red (6)), and 'MMS'. On the right, the 'Date & Time' section shows Date: 2021/04/13 and Time: 15:15. Below it, the 'Time Zone' section shows (GMT+01:00) Brussels, Copenhagen, Madrid, Paris. The 'Internet Time' section has 'Automatically synchronize with an internet time server.' unchecked and 'Server' set to (Disable), with 'OK' circled in red (8). The navigation menu on the right shows 'System Setting' > 'Date & Time' circled in red (7).

Du kan nu benytte alarmen uden LAN-forbindelse